arXiv:physics/0610198v1 [physics.optics] 23 Oct 2006

SIMULTANEOUS NEGATIVE– AND POSITIVE–PHASE–VELOCITY PROPAGATION IN AN ISOTROPIC CHIRAL MEDIUM

Tom G. Mackay[1] **and Akhlesh Lakhtakia**[2]

[1] School of Mathematics
University of Edinburgh
Edinburgh EH9 3JZ, United Kingdom

[2] CATMAS — Computational & Theoretical Materials Sciences Group
Department of Engineering Science & Mechanics
212 Earth & Engineering Sciences Building
Pennsylvania State University, University Park, PA 16802–6812

ABSTRACT: The phase velocity of plane waves propagating in an isotropic chiral medium can be simultaneously positive for left–circularly polarized light and negative for right–circularly polarized light (or vice versa). The constitutive parameter regimes supporting this phenomenon are established for nondissipative and dissipative mediums. The boundary between positive and negative phase velocity is characterized by infinite phase velocity.

Keywords: *negative refraction, positive refraction, infinite phase velocity*

1. INTRODUCTION

An isotropic chiral medium is characterized in the frequency domain by the Tellegen constitutive relations

$$\mathbf{D} = \epsilon_0 \epsilon_r \, \mathbf{E} + i\sqrt{\epsilon_0 \mu_0}\, \kappa \, \mathbf{H} \,, \tag{1}$$

$$\mathbf{B} = \mu_0 \mu_r \, \mathbf{H} - i\sqrt{\epsilon_0 \mu_0}\, \kappa \, \mathbf{E} \,, \tag{2}$$

wherein ϵ_r, μ_r, and κ are frequency–dependent complex–valued scalars, whereas ϵ_0 and μ_0 are the permittivity and permeability of free space (i.e., vacuum).

Electromagnetic waves in this medium are best described using left– and right–handed Beltrami fields [1]

$$\mathbf{Q}_L = \mathbf{E} + i\frac{\sqrt{\mu_0}}{\sqrt{\epsilon_0}}\,\frac{\sqrt{\mu_r}}{\sqrt{\epsilon_r}}\,\mathbf{H}\,, \tag{3}$$

$$\mathbf{Q}_R = \mathbf{E} - i\frac{\sqrt{\mu_0}}{\sqrt{\epsilon_0}}\,\frac{\sqrt{\mu_r}}{\sqrt{\epsilon_r}}\,\mathbf{H}\,, \tag{4}$$

such that

$$\nabla\times\mathbf{Q}_L = k_L\,\mathbf{Q}_L\,, \quad k_L = k_0(\sqrt{\epsilon_r}\sqrt{\mu_r}+\kappa)\,, \tag{5}$$

$$\nabla\times\mathbf{Q}_R = -\,k_R\,\mathbf{Q}_R\,, \quad k_R = k_0(\sqrt{\epsilon_r}\sqrt{\mu_r}-\kappa)\,. \tag{6}$$

Examining plane–wave propagation in an isotropic chiral medium, Mackay [2] obtained the conditions to delineate negative–phase–velocity (NPV) and positive–phase–velocity (PPV) propagation therein. Those conditions led to the following question: Can an isotropic chiral medium simultaneously support NPV and PPV propagation? If the answer is in the affirmative, an isotropic chiral slab could behave like the so–called perfect lens for right–circularly polarized (RCP) light from a certain source but not for left–circularly polarized (LCP) light from that same source (or vice versa) [3].

2. ANALYSIS

Let us begin with the nondissipative scenario wherein ϵ_r, μ_r, and κ are all real–valued. The restriction $\epsilon_r\mu_r > 0$ is imposed to exclude evanescent plane waves from consideration. We have that

$$|\kappa| < \left|\sqrt{\epsilon_r}\sqrt{\mu_r}\right| \quad \Rightarrow \quad \left.\begin{array}{l}\text{LCP and RCP plane waves are of the PPV type for } \epsilon_r > 0\\ \text{LCP and RCP plane waves are of the NPV type for } \epsilon_r < 0\end{array}\right\}\,,$$

while

$$-\kappa > \left|\sqrt{\epsilon_r}\sqrt{\mu_r}\right| \quad \Rightarrow \quad \left.\begin{array}{l}\text{LCP plane waves are of the NPV type}\\ \text{RCP plane waves are of the PPV type}\end{array}\right\}$$

and

$$\kappa > \left|\sqrt{\epsilon_r}\sqrt{\mu_r}\right| \quad \Rightarrow \quad \left.\begin{array}{c}\text{LCP plane waves are of the PPV type}\\ \text{RCP plane waves are of the NPV type}\end{array}\right\} .$$

Thus, when

$$|\kappa| > |\sqrt{\epsilon_r}\sqrt{\mu_r}| \,, \tag{7}$$

the nondissipative isotropic chiral medium simultaneously supports both PPV and NPV plane–wave propagation. The transition from PPV to NPV (or vice versa) arises as the relevant wavenumber (k_L or k_R) passes through zero. Therefore, the PPV/NPV boundary is characterized by the magnitude of the phase velocity becoming infinite, as has been reported previously for isotropic dielectric–magnetic mediums [4].

Next we turn to the dissipative scenario wherein ϵ_r, μ_r, and κ are all complex–valued. The wavenumbers lie in the upper half of the complex plane, as dictated by the Kramers–Kronig relations [5]. Let us consider the regimes $\rho > 0$ and $\rho < 0$, where[1]

$$\rho = \frac{\mathrm{Re}\,\{\epsilon_r\}}{\mathrm{Im}\,\{\epsilon_r\}} + \frac{\mathrm{Re}\,\{\mu_r\}}{\mathrm{Im}\,\{\mu_r\}} \tag{8}$$

is the NPV parameter for isotropic dielectric–magnetic mediums [6]. We find

$$|\mathrm{Re}\,\{\kappa\}| < \mathrm{Re}\left\{\sqrt{\epsilon_r}\sqrt{\mu_r}\right\} \quad \Rightarrow \quad \left.\begin{array}{c}\text{LCP and RCP plane waves are of the PPV type for } \rho > 0\\ \text{LCP and RCP plane waves are of the NPV type for } \rho < 0\end{array}\right\} ,$$

whereas

$$-\mathrm{Re}\,\{\kappa\} > \mathrm{Re}\left\{\sqrt{\epsilon_r}\sqrt{\mu_r}\right\} \quad \Rightarrow \quad \left.\begin{array}{c}\text{LCP plane waves are of the NPV type}\\ \text{RCP plane waves are of the PPV type}\end{array}\right\}$$

and

$$\mathrm{Re}\,\{\kappa\} > \mathrm{Re}\left\{\sqrt{\epsilon_r}\sqrt{\mu_r}\right\} \quad \Rightarrow \quad \left.\begin{array}{c}\text{LCP plane waves are of the PPV type}\\ \text{RCP plane waves are of the NPV type}\end{array}\right\} .$$

Therefore, the dissipative medium simultaneously supports both PPV and NPV plane–wave propagation when

$$|\mathrm{Re}\,\{\kappa\}| > \mathrm{Re}\,\{\sqrt{\epsilon_r}\sqrt{\mu_r}\} \,. \tag{9}$$

---

[1] The operators Re { • } and Im { • } deliver the real and imaginary parts of their complex–valued arguments.

The PPV/NPV boundary occurs where the real part of the relevant wavenumber passes through zero and the magnitude of the phase velocity correspondingly becomes unbounded [4].

3. CONCLUDING REMARKS

When the magnitude of the real part of its relative magnetoelectric parameter κ is sufficiently large relative to the magnitudes of the real parts of its relative permittivity ϵ_r and relative permeability μ_r, an isotropic chiral medium can simultaneously support both PPV and NPV plane–wave propagation, with different circular polarization states. Large values of κ are difficult to realize [7], and perhaps the best option to simultaneously propagate NPV and PPV plane waves in an isotropic chiral material would be to focus on realizing $|\epsilon_r| < 1$ and $|\mu_r| < 1$ [8].

Acknowledgment: TGM is supported by a *Royal Society of Edinburgh/Scottish Executive Support Research Fellowship.*

References

[1] A. Lakhtakia, Beltrami fields in chiral media, World Scientific, Singapore, 1994.

[2] T.G. Mackay, Plane waves with negative phase velocity in isotropic chiral mediums, Microw Opt Technol Lett 45 (2005), 120–121; corrections: 47 (2005), 406.

[3] J.B. Pendry, A chiral route to negative refraction, Science 306 (2004), 1353–1355.

[4] A. Lakhtakia and T.G. Mackay, Infinite phase velocity as the boundary between positive and negative phase velocities, Microw Opt Technol Lett 41 (2005), 165–166.

[5] C.F. Bohren and D.R. Huffman, Absorption and scattering of light by small particles, Wiley, New York, NY, USA, 1983.

[6] R.A. Depine and A. Lakhtakia, A new condition to identify isotropic dielectric–magnetic materials displaying negative phase velocity, Microwave Opt Technol Lett 41 (2004), 315–316.

[7] C.F. Bohren, Isotropic chiral materials, In: W.S. Weiglhofer and A. Lakhtakia (eds), Introduction to complex mediums for electromagnetics and optics, SPIE Press, Bellingham, WA, USA, 2003.

[8] A. Lakhtakia and T.G. Mackay, Fresnel coefficients for a permittivity–permeability phase space encompassing vacuum, anti–vacuum, and nihility, Microw Opt Technol Lett 48 (2006), 265–270.